



BORE TECH
REDEFINING GUN CARE

AR RECEIVER CLEANING KIT DIRECTIONS



www.boretech.com
cs@boretech.com

1

A. Separate Lower & Upper.
B. Field strip Bolt Carrier Group (BCG).

2

A. Scrape bolt tail in rear of carrier tool to remove heavy fouling.
B. Scrape bolt carrier w/ front of carrier tool to remove heavy fouling.

3

Place BCG parts in plastic container and soak with C4 Carbon Remover (C4).

4

A. Pack a patch soaked w/ C4 underneath & around gas tube area w/ the provided pick & let soak.
B. Let BCG parts and gas tube area soak while cleaning the barrel.

5

After cleaning barrel:

A. Brush chamber using C4, chamber brush, rod & guide.
B. Brush upper using C4, upper brush, rod, & guide.
C. Brush remaining areas w/ C4 & Gun Brush.

6

A. Dry chamber w/ loop & patch.
B. Dry inside barrel extension w/ cross wiper & patch.
C. Dry upper w/ round wiper & patch. (can also be used to clean buffer tube).

7

A. Remove wet patch from gas tube area w/ pick.
B. Dry gas tube area & charging handle recess w/ pick, patch & swab where needed.

8

Remove BCG parts from container.
A. Scrape firing pin.
B. Brush/clean all BCG parts.
C. Swab inside of bolt.

9

A. Polish bolt tail w/ green pad in rear of carrier tool.
B. Dry off bolt tail w/ patch in rear of carrier tool.

10

A. Polish inside bolt carrier w/ green pad. Refer to Figure A (to the right) for how to insert pad into tool.
B. Dry out bolt carrier w/ patch. Refer to Figure B (to the right) for how to insert patch into tool.

11 & 12

11. Dry rear of bolt carrier w/ loop & patch. Refer to Figure B (to the right) for how to insert patch into loop.
12. Lubricate & reassemble BCG. Reassemble Upper & Lower. Cycle bolt to ensure proper operation.

Fig. A

INSERT
TWIST 90

Fig. B

*FOLD OVER
INSERT
*FOLD OVER

FOR PRODUCT VIDEOS & MORE VISIT OUR WEBSITE: www.boretech.com

Bore Stix, C4 Carbon Remover, & Bore Guide not Included